

#### FEATURES



Our T8 LED tube can work with the most popular electronic ballasts that are capable of replacing your existing fluorescent T8 lamps without any additional wiring. It provides exceptional LED lighting with reduced energy and maintenance costs.

- **Plug & Go™ - Works with existing electronic ballast\***
- Wide beam design - 240° light emitting area
- Exceptional efficacy
- No flickering
- Safety Glass

*\*\*Suitable for dimming and emergency ballasts.*

#### SPECIFICATIONS


<b>Power Consumption</b>	<b>18W</b>
Input Voltage	120-277V
Power Factor	0.9
Lumens	1850
Luminous Efficiency	103 Lm/W
Color Temperature	3500K
CRI	81
LED Quantity	90
Beam Angle	240°
Average Life	50,000
Dimension (Inches)	47.2"(L) x 1"(DIA)

**SAFETY COATED**

SUITABLE FOR  
**DAMP LOCATIONS**



#### DIMENSIONS



#### ORDERING

ITEM#	DESCRIPTION	WATT	LED	LED QTY	COLOR	LUMENS	CRI	VOLT	HOURS	CASE	
CLR/LLR143	LED 4' 18WT8/35K/FR/V4/SAFETY COATED	90585	18	SMD	90	3500K	1850	81	120-277V	50,000	25